

Program: B.Tech. (Electronics and Telecommunication)				
Examination: 1Y Semester: V				
Course Code: EXC503 and Course Name: Discrete Time Signal Processing				
Duration: 2.5 Hours				
Instructions:				Max. Marks: 60
(1) All questions are compulsory. (2) Draw neat diagrams wherever applicable. (3) Assume suitable data, if necessary.				
		Max. Marks	CO	BT level
Q 1	Solve any six questions out of eight:	12		
i)	Explain ECG signal analysis	02	6	U
ii)	Find DFT of $\delta(n)$	02	2	U
iii)	Why a band-reject filter is called a notch filter?	02	1	U
iv)	Compare Symmetric and Anti-symmetric FIR filter	02	3	U
v)	What is frequency wrapping? How its effect can be eliminated?	02	3	U
vi)	State and explain quantization noise	02	5	U
vii)	Explain Frequency sampling structure of FIR system	02	4	U
viii)	Compare DIT and DIF algorithm	02	2	U
Q.2	Solve any four questions out of six.	16		
i)	Obtain $H(z)$ from $H(s)$ when $T=1$ sec and $H(s) = \frac{1}{s^2+2s+1}$, using Bilinear transformation	04	3	A
ii)	State and prove linearity property of DFT	04	2	U
iii)	Explain Gibb's phenomenon	04	3	U
iv)	Realize the filter transfer function, $(z) = \frac{1}{(1+2z^{-1})(1-z^{-2})}$.	04	5	A
v)	Perform circular convolution of the sequences, $x_1(n) = \{2, 2, 6, 1\}$ and $x_2(n) = \{1, 1, 3, 4\}$	04	2	U
vi)	State how DSP can be used for Dual Tone Multi-Frequency Signal Detection.	04	6	U

K. J. Somaiya Institute of Technology, Sion, Mumbai-22
(Autonomous College Affiliated to University of Mumbai)

Subject Code: **EXC503** Subject Name: **Discrete Time Signal Processing** Date: 10/08/23

Q.3	Solve any two questions out of three.	16		
i)	Design a Butterworth digital IIR low pass filter using Bilinear transformation by taking sampling frequency 8 KHz, to satisfy the following specifications. $0.85 \leq H(e^{j\omega}) \leq 1 \quad : \quad 0 \leq \omega \leq 0.25\pi$ $ H(e^{j\omega}) \leq 0.13 \quad : \quad 0.63\pi \leq \omega \leq \pi$	08	3	A
ii)	Explain Truncation and Rounding method with graph.	08	5	U
iii)	Explain Short Time Spectral Analysis of Speech signal using DSP	08	6	U
Q.4	Solve any two questions out of three.	16		
i)	Obtain the cascade structure of the FIR filter, defined by the transfer function, $H(z) = (a_0 + a_1z^{-1} + a_2z^{-2})(b_0 + b_1z^{-1})$	08	4	U
ii)	Draw ideal and actual frequency response characteristics of various types of filters and explain each in brief.	08	1	A
iii)	Compute 8-point DFT of $x(n) = (1, 4, 3, 3, 8, 1, 7, 2)$ by radix-2 DIT-FFT.	08	2	A
